

For Unicode Message:

Promotional Unicode Message API

<http://cloud.smsindiahub.in/vendorsms/pushsms.aspx?user=yourUserID&password=yourPassword&msisdn=919898xxxxxx&sid=SenderId&msg=परीक्षण संदेश &fl=0&dc=8>

Transactional Unicode Message API

<http://cloud.smsindiahub.in/vendorsms/pushsms.aspx?user=yourUserID&password=yourPassword&msisdn=919898xxxxxx&sid=SenderId&msg=परीक्षण संदेश &fl=0&dc=8&gwid=2>

Note: Please define Dynamic Value in ##Field##

The following are the parameters used:

Parameter name	Parameter Value	Description
User	abc	your user name
password	xyz	your password
msisdn	919898123456	Destination mobile number
sid	WEBSMS	Sender ID
msg	This is test sms from SMS INDIA HUB	Msg to be Sent
fi	0	Flast Message Indicator 1 for Yes and 0 for No
dc	8	For any regional Language

Response:

Single Message

Recipient's Mobile number, the date stamp and a unique ID.

The Message Id : 919898123456-200612295008123

Multiple Message

The Message Id : 919898123456-200612295008123

The Message Id : 919898001234-200612295008924

Cloud Wireless Technologies India Pvt. Ltd.

Plot No. 16, Rajat Business Chamber, Opp. GK Palace Hotel,
MP Nagar - Zone - II - Bhopal - Pin - 462011
Phone : +(91) 755 3315000 | +(91) 755 3315005 | +(91) 755 4287270

Email: info@smsindiahub.in | support@smsindiahub.in | sales@smsindiahub.in | reseller@smsindiahub.in

www.smsindiahub.in | www.solutionsbox.co.in | www.websitedesignwala.in | www.smppapplication.in | www.mail-server-in



Message parameter details

Username (user)

The username value is passed for authentication purposes. The username is provided to the client when he registers for the HTTP API option from smsindiahub. In. The username (user) parameter cannot be more than 20 characters long and can only contain alphabets and numbers, with no spaces or special characters.

Password (password)

The password parameter value is also passed in combination with the username for authentication purposes. The password is provided to the client along with the username when he registers with Smsindiahub. In for sending SMS messages Through the Gateway. The password (pass) parameter cannot have more than 20 Characters and can contain only alphabets and numbers, with no spaces or Special characters.

Mobile Number (msisdn)

The mobile number parameter refers to the destination mobile number to which the message is to be sent. However, the mobile number is required to be in a Specific format. Any error in this parameter value would lead to non-delivery of the message. The mobile number should contain only numbers. It must also include the country code at the start beginning. It should not contain any Symbols (+) or 00 etc. and it must be a valid mobile number supported by the smsindiahub.in Gateway (All Indian Cellular Operators).

Message (msg)

The message parameter refers to the actual message that is to be sent to the destination mobile (msisdn). The behavior of the message parameter differs depending on the type of message being sent. The message parameter may consist of up to 160 characters belonging to the following set:

- A Z a...z 0...9
- Blank space
- The meta characters \ (line feed)

Due to restrictions in the HTTP protocol format, the following special characters

must be encoded in order not to collide with reserved HTTP characters:

Cloud Wireless Technologies India Pvt. Ltd.

Plot No. 16, Rajat Business Chamber, Opp. GK Palace Hotel,
MP Nagar - Zone - II - Bhopal - Pin - 462011
Phone : +(91) 755 3315000 | +(91) 755 3315005 | +(91) 755 4287270

Email: info@smsindiahub.in | support@smsindiahub.in | sales@smsindiahub.in | reseller@smsindiahub.in

www.smsindiahub.in | www.solutionsbox.co.in | www.websitedesignwala.in | www.smppapplication.in | www.mail-server-.in

Character must be encoded as:

Character	Hexa-decimal Encoded String
&	%26
+	%2B
%	%25
#	%23
=	%3D

For simple text messages, the message can contain numbers, alphabets, and spaces and certain special characters. However, the message can contain a maximum of 160 characters, including spaces.

In case of maximum number of characters exceed 160, message is treated as Long Message (Concatenated SMS) and is automatically split in multiple parts Based on the length of the SMS. Our gateway can support maximum up to 459 Characters of Long Message.

Note: In case of Long Message, credits are deducted accordingly.

Valuable Facts:

1. According to GSM specification, a standard SMS message can contain up to 140 bytes of data (payload).
2. GSM encoding represents characters using 7 bits instead of 8. This Therefore provides a maximum of 160 characters per SMS.

(140 * 8 bits) / 7 bits = 160 Character

3. A Concatenated SMS is formed from several standard SMS containing a 7 byte concatenation header (contains the information of various parts of the Message) at the beginning of each one. Since this 7 byte header is within the Message, it reduces the total size of each SMS to 153 characters each.

Number of SMS	Max Length
1	160
2	306
3	459
4	612
5	765
6	918
7	1072
8	1220

Cloud Wireless Technologies India Pvt. Ltd.

Plot No. 16, Rajat Business Chamber, Opp. GK Palace Hotel,
MP Nagar - Zone - II - Bhopal - Pin - 462011
Phone : +(91) 755 3315000 | +(91) 755 3315005 | +(91) 755 4287270

Email: info@smsindiahub.in | support@smsindiahub.in | sales@smsindiahub.in | reseller@smsindiahub.in

www.smsindiahub.in | www.solutionsbox.co.in | www.websitedesignwala.in | www.smpapplication.in | www.mail-server-.in



Sender Id (sid)

The sender Id parameter refers to the message dispatcher or from clause (THE SENDER), from whom the message is sent. The sender Id can either be a valid international number up to sixteen characters long or an eleven character alphanumeric string. The sender Id is an optional clause. In case the sender Id is not specified, the SMSC number is sent as the sender Id to the destination mobile

Sender Id in case of text messaging can only be made up of alphabets & digits. It cannot contain any special characters such as (-,+) etc.

Flash Message (fl)

Flash message parameter indicates whether the message will be a flashed on the destination mobile (msisdn). It can contain only the values (0 or 1). Default value for this parameter is 0. When the flash parameter is sent as 1 (fl=1), the SMS message is flashed on the destination mobile.

Value Description

0 Don't flash message.

1 Flash message on destination mobile screen

Error Message

The following are the error messages returned by the smsindiahub. In gateway in Case of Invalid parameters provided.

Error Code	Error Message
0	Success (it means message is successfully submitted and you can check message parameter response to check message id and parts)
1	Account details cannot be blank
2	Username or password cannot be blank
3	SenderId cannot be blank
4	Message cannot be blank
5	Message properties cannot be blank
6	ServerError#Error message
7	Invalid username or password
8	Account inactive
9	Account lock
10	Unauthorized API access
11	Unauthorized IP address
12	Message length violation
13	Invalid mobile numbers
14	Account locked due to spam message contact support
15	Invalid SednerId

Cloud Wireless Technologies India Pvt. Ltd.

Plot No. 16, Rajat Business Chamber, Opp. GK Palace Hotel,

MP Nagar - Zone - II - Bhopal - Pin - 462011

Phone : +(91) 755 3315000 | +(91) 755 3315005 | +(91) 755 4287270

Email: info@smsindiahub.in | support@smsindiahub.in | sales@smsindiahub.in | reseller@smsindiahub.in

www.smsindiahub.in | www.solutionsbox.co.in | www.websitedesignwala.in | www.smpapplication.in | www.mail-server-in



Technologies India Pvt Ltd.

16	Transactional account not active
17	Invalid groupid
18	Cannot send multi message to group
19	Invalid schedule date
20	Message or mobile number cannot be blank
21	Insufficient credits
22	Invalid jobid
23	Parameter missing
24	Invalid template or template mismatch

Note: Only the above-defined validations are performed at the server side.

All other validations for any parameter are required to be handled at the Client side explicitly.

Thanks

Tech Team SMS INDIA HUB
Support@smsindiahub.in

Cloud Wireless Technologies India Pvt. Ltd.

Plot No. 16, Rajat Business Chamber, Opp. GK Palace Hotel,
MP Nagar - Zone - II - Bhopal - Pin - 462011
Phone : +(91) 755 3315000 | +(91) 755 3315005 | +(91) 755 4287270

Email: info@smsindiahub.in | support@smsindiahub.in | sales@smsindiahub.in | reseller@smsindiahub.in

www.smsindiahub.in | www.solutionsbox.co.in | www.websitedesignwala.in | www.smppapplication.in | www.mail-server-.in



Technologies India Pvt Ltd.